

# Essential Theory and Concepts of Signal Processing Volume II

Edited by George Pilato



**Essential Theory and Concepts of Signal Processing Volume II** 

## **Preface**

Signal processing is a part of the fields of electrical engineering, systems engineering and applied mathematics that deals with analysis of or operations on analog as well as digitized signals which represent spatially varying or time-varying physical quantities. Signal Processing can also be said to be the art and science of adapting obtained time-series data for the purpose of breakdown, analysis and augmentation. Signals of interest usually include sound, images, electromagnetic radiation and sensor readings. Such signals can be lifted from various machines and instances in the real world, for example, from biological measurements such as electrocardiograms, telecommunication transmission signals, control system signals and many others. Signal processing has various applications in the real world such as audio signal processing for electrical signals representing sound; image processing in digital cameras, computers and various imaging systems; wireless communication via filtering, waveform generation, equalization and demodulation; array processing for processing signals from arrays of sensors; video processing for interpreting moving pictures; quality improvement of signal like image enhancement, noise reduction and echo cancellation; and even control systems and seismology. Such applications for this field in our daily lives underline the importance of signal processing in the industry today. Therefore the rising demand for skilled graduates in this arena is keeping up its emergence in the global industry.

This book is an attempt to compile and collate all available research on signal processing under one aegis. I am grateful to those who put their hard work, effort and expertise into these researches as well as those who were supportive in this endeavour.

Editor

# Contents

	Preface	VI
Chapter 1	Studies on Z-Window Based FIR Filters Rahul Pachauri, Rajiv Saxena and Sanjeev N. Sharma	1
Chapter 2	Weather Forecasting Using Sliding Window Algorithm Piyush Kapoor and Sarabjeet Singh Bedi	9
Chapter 3	Extraction of Correlated Sparse Sources from Signal Mixtures M. S. Woolfson, C. Bigan, J. A. Crowe and B. R. Hayes-Gill	14
Chapter 4	Spatial Resolution Analysis for Few-Views Discrete Tomography Based on MART-AP Algorithm Alexander B. Konovalov and Vitaly V. Vlasov	31
Chapter 5	Instantaneous Granger Causality with the Hilbert-Huang Transform João Rodrigues and Alexandre Andrade	38
Chapter 6	A Review of Subspace Segmentation: Problem, Nonlinear Approximations, and Applications to Motion Segmentation Akram Aldroubi	47
Chapter 7	Dynamically Measuring Statistical Dependencies in Multivariate Financial Time Series Using Independent Component Analysis Nauman Shah and Stephen J. Roberts	60
Chapter 8	A Novel Optimized Golomb-Rice Technique for the Reconstruction in Lossless Compression of Digital Images Shaik. Mahaboob Basha and B. C. Jinaga	74
Chapter 9	Keystroke Dynamics User Authentication Based on Gaussian Mixture Model and Deep Belief Nets Yunbin Deng and Yu Zhong	79
Chapter 10	About a Partial Differential Equation-Based Interpolator for Signal Envelope Computing: Existence Results and Applications Oumar Niang, Abdoulaye Thioune, Éric Deléchelle, Mary Teuw Niane and Jacques Lemoine	86
Chapter 11	Single Channel Speech Enhancement Using Adaptive Soft-Thresholding with Bivariate EMD Md. Ekramul Hamid, Md. Khademul Islam Molla, Xin Dang and Takayoshi Nakai	104

**List of Contributors** 

Chapter 12	NGFICA Based Digitization of Historic Inscription Images Indu Sreedevi, Rishi Pandey, N. Jayanthi, Geetanjali Bhola and Santanu Chaudhury	113
Chapter 13	A Novel Neuron in Kernel Domain Zahra Khandan and Hadi Sadoghi Yazdi	120
Chapter 14	<b>Design of Adjustable Square-Shaped 2D IIR Filters</b> Radu Matei	131
Chapter 15	Two-Channel Quadrature Mirror Filter Bank: An Overview S. K. Agrawal and O. P. Sahu	141
Chapter 16	Recovery of Missing Samples with Sparse Approximations Benjamin G. Salomon	151
Chapter 17	High-Resolution Direction-of-Arrival Estimation via Concentric Circular Arrays Serdar Ozgur Ata and Cevdet Isik	156
Chapter 18	Adaptive Selection Combining Receiver over Time Varying Frequency Selective Fading Channel in Class-A Noise Ahmed El-Sayed El-Mahdy	164
Chapter 19	Anisotropic Diffusion for Details Enhancement in Multiexposure Image Fusion Harbinder Singh, Vinay Kumar and Sunil Bhooshan	170
	Permissions	

# Studies on Z-Window Based FIR Filters

### Rahul Pachauri, 1 Rajiv Saxena, 1 and Sanjeev N. Sharma 2

Department of Electronics & Communication Engineering, Jaypee University of Engineering & Technology, Guna 473226, India

<sup>2</sup> Department of Electronics & Communication Engineering, Samrat Ashok Technological Institute, Vidisha 464001, India

Correspondence should be addressed to Rahul Pachauri; pachauri.123@gmail.com

Academic Editors: I. Guler and C. S. Lin

As per classification of the window functions, the Z-windows are grouped in the category of steerable side-lobe dip (SSLD) windows. In this work, the application of these windows for the design of FIR filters with improved filter parameters has been explored. The numbers of dips with their respective positions in the side-lobe region have been compositely used to tailor the window shape. Filter design relationships have been established and included in this paper. Simultaneously, an application of these Z-window based FIR filters in designing two-channel quadrature mirror filter (QMF) bank has been presented. Better values of reconstruction and aliasing errors have been achieved in contrast to the Kaiser window based QMF bank.

#### 1. Introduction

The finite impulse response (FIR) filters are one of the prominent building blocks used in various applications of digital signal processing. These filters have got more popularity than infinite impulse response (IIR) filters because of their inherent stability and linear phase characteristics [1]. The straightforward approach to design the FIR filters is truncating the ideal impulse response using windows. Careful selection of window function reduces the ripples introduced by truncation in the frequency response of these filters [2]. In the literature, several categories of windows have been proposed [3, 4]. One of the important categories of windows is steerable side lobe dips (SSLD) windows in which deep dips can be steered in the side lobes. Tseng windows and Zhong windows (ZWs) are the examples of SSLD windows [5, 6]. The ZW proposed by Zhong et al. [6] has simple expressions in either of the domains, good overall spectral characteristics, SSLD property and easy and flexible design technique as compared to Tseng window. These features of ZW motivated us to study this window from the FIR filter design perspective.

Prior to this work, the design of FIR filters using ZW has also been reported by Sharma et al. [7] in which filter order (N) and transition bandwidth (TBW) have been minimized at the cost of higher passband ripple (PBR) and stopband attenuation (SBA). The filters designed by Sharma et al. [7] are having SBA in the range of  $18-42 \, \mathrm{dB}$  with single dip steered

at an appropriate location in the side lobes of ZW. Followed by this work, the ZW filter (ZWF) has been designed using the traditional window based approach by Pachauri et al. [8] in which the PBR and SBA has been minimized at the cost of higher filter order. The expression of the filter order was modified in [8] and was made directly proportional to the number of SSLDs introduced in the ZW. It has also been demonstrated in [8] that the half main lobe width (HMLW) of ZW varies with dip displacement up to a certain position and after that it becomes constant. If the dips are introduced below this threshold position then the filter order reduces and PBR and SBA increase [7], whereas the filter order increases and PBR and SBA decrease when the dips are inserted on the other side of the threshold position [8]. With this background on spectral response of ZW, the studies available in [7, 8], low pass filters have been designed using Z-window in this work. Performance of these filters has been studied by varying number of dips in ZW along with respective variation in their position. This study helped us in establishing an application of this filter in multirate signal processing.

The remaining part of this paper has been organized as follows. In the next section ZW has been introduced and its properties from the filter design perspective have been discussed. In Section 3, an algorithm to establish the empirical design relationships for ZWF has been developed. Simulation results and the performance analysis of the proposed filters are included in Section 4. Design of quadrature mirror filter

(QMF) bank using this filter as a prototype has been carried out in Section 5. A comparative study with Kaiser window (KW) based QMF bank has also been performed. Finally, the paper is concluded in Section 6.

# 2. Characterization of Z-Window for Filtering Application

The basic concept in ZW proposed by Zhong et al. [6] is that the spectral window can be considered as a special LPF which only passes the DC component. The technique used for the designing of ZW is based on the frequency sampling method used for FIR filter design.

The ZW of length N with L SSLDs has been defined as [6]

$$w(n) = \frac{1}{0.5 + \sum_{k=1}^{L} x_k} \left[ 0.5 + \sum_{k=1}^{L} (-1)^k x_k \cos\left(\frac{(2n+1)\pi k}{N}\right) \right]$$
 for  $n = 0, 1, \dots, N-1$ , (1)

where,

$$x_{k} = \cos \frac{\pi k}{N} \left[ \prod_{l=1}^{L} \left( 1 - \cot^{2} \frac{\omega_{l}}{2} \tan^{2} \frac{\pi k}{N} \right) \right]$$

$$\times \left( 2 \left[ \prod_{i=1}^{k-1} \left( \cot^{2} \frac{\pi i}{N} \tan^{2} \frac{\pi k}{N} - 1 \right) \right]$$

$$\cdot \left[ \prod_{i=k+1}^{L} \left( 1 - \cot^{2} \frac{\pi i}{N} \tan^{2} \frac{\pi k}{N} \right) \right] \right)^{-1}$$

$$\text{for } k = 1, 2, \dots, L.$$

$$(2)$$

In this window, instead of traditional approach to minimize the maximum side-lobe level (MSLL) with steepest descent or linear programming [9, 10], dips have been introduced at frequencies  $\omega_l$ ,  $l=1,\ldots,L$ , masking the magnitude spectrum  $|W(e^{j\omega})|$  of the window at these frequencies.

A window of length N may have L dips which must satisfy the following conditions:

$$\pi > \omega_l > \frac{2\pi L}{N},\tag{3}$$

$$x_1 > x_2 > \dots > x_L > 0,$$
 (4)

$$x_k < \frac{(L!)^2}{(L+k)! \cdot (L+k)!} < 1.$$
 (5)

Condition (3) tells us that apart from finite set of frequencies:  $(2\pi(L+1)/N,\ldots,2\pi M/N,\text{ for }M=\{^{(N-1)/2}, ^{N}\text{ odd}_{N/2}, ^{N}\text{ even})$ , where zeros of  $|W(e^{j\omega})|$  already exist,  $\omega_l$  can be assigned anywhere in the side lobes region, that is,  $(2\pi L/N,\pi)$ . The meaningfulness of the solution is guaranteed by (4) and (5) as they give the upper bound of the solutions.

It has already been shown in [6] that by steering number of dips and their respective positions in the side lobes of ZW,




Figure 1: Plot for illustrating the definition of the various parameters of Z-window with N=51, L=1, and dip at 5.6.

the characteristics of the window, that is, HMLW, MSLL, and side lobe fall of rate (SLFOR), can be varied. To illustrate the above parameters, a ZW with one steerable dip is shown in Figure 1. The normalized frequency in bins, which has been used to label the *x*-axis of the magnitude spectrum of ZW, has been defined as [11]

frequency in bins 
$$f_k = \frac{kF_s}{N}$$
 for  $k = 0, 1, ..., N - 1$ ,

(6)

where N is the window length and  $F_s$  is the sampling frequency.

Other important properties of ZW given in [6, 8] and observed in this work are as follows.

- (i) The dips can be steered in the side lobes anywhere between bins 1 and N/2 [6].
- (ii) The HMLW, MSLL, and SLFOR can be varied by varying the number of dips and their position in the side lobes. This follows from the simulation plots shown in Figures 2 and 3.
- (iii) The HMLW increases linearly with the increase in position of dips initially and after that it becomes constant [8].
- (iv) The MSLL decreases with position of dips, initially linearly, and after that it becomes almost constant. This behavior of MSLL is shown in Figure 4.
- (v) It follows from Figures 1 and 2 that if the dips are inserted in the vicinity of N/2 the HMLW and SLFOR are higher, while MSLL is higher than the minimum value which follows from Figure 4. This property has been used in this work to obtain ZWF with maximum value of far end stopband attenuation (FESBA).

The above listed properties of Z-window function are directly associated with the design of FIR filters. Thus,




FIGURE 2: Variation of MSLL and SLFOR of ZW by insertion of one dip for a window of length N=61.




FIGURE 3: Variation of MSLL and SLFOR of ZW by insertion of two dips in a window of length N=61.

these properties of ZW have been exploited in this work to design FIR filters. In the proposed work, new empirical design relationships have been derived which provide more flexibility to vary the design parameters of ZWF, keeping desired specifications intact.

#### 3. Filter Design Relationships

To design an FIR filter using window functions the following relationships are required [11].




FIGURE 4: Variation of MSLL with position of dips for a window of length N=51.


- (a) Relationship between SBA  $(A_s)$  and window shape parameter—this expression provides the value of window shape parameter for the desired SBA. In ZW, SSLD property, that is, number of dips L and their position  $D_p$ , has been used to tailor the window shape.
- (b) Expression defining the relationship between SBA  $(A_s)$  and normalized window width parameter (D) [12–14]—this value of D is then used to calculate the filter order N to provide the desired filter transition bandwidth (TBW;  $\Delta f$ ), at a specified sampling frequency  $(F_s)$ . The value of N is given by

$$N \ge \frac{D}{\Delta f/F_s} + 1. \tag{7}$$

To establish these relationships for the design of FIR low pass filters with ZW, the parameters, namely, L,  $D_p$ , and N, were varied. The resulting variation in A, and D is recorded in Table 1 and corresponding plots are shown in Figures 5 and 6. From these plots the empirical relations between D, L,  $D_p$ , and A, have been obtained. The procedure for establishing these relationships has been described with the aid of a flow chart shown in Figure 7. Conventionally, in window based FIR filter designs, filter order N is initialized to a very large value and for this fixed value of N design relationships are enumerated [12-14]. However, in this study, instead of using fixed N it has been taken as a variable. Therefore, in this work variations in the values of D and SBA have been obtained by varying the number of dips and their positions as well as the filter order N. The filter order and the number of dips have been used to change D and A, when these parameters become insensitive to a further increase in the dip position as shown in Table 1. The empirical relations have been obtained

TABLE 1: Observations to establish design relationships for ZWF.

Number of dips, $L$	Position of dips, $D_p$	Filter order, N	Normalized window width, ${\cal D}$	Stopband attenuation, $A_s$ (dB)
	1	17	1.576	16.93
1	1.1	21	2.09	20.61
	1.6	35	3.35	38.89
	1.7	37	3.61	42.57
2	2	47	4.53	44.12
-	2.6	57	5.73	60,73
3	3	69	6.74	61.09
	3.8	79	7.87	76.66
4	4	91	8.98	78.49
1	4	99	9.84	90.34
5	5	111	11.03	93.28
	5	121	11.95	105.67
6	6	131	13.04	107.82
	6	141	13.92	118.93
7	7	151	15.05	121.36
*	7	161	15.91	132.82
8	8	171	17.04	135.27
0	8	181	17.91	146.78
9	9	191	19.05	149.31
	9	199	19.89	160.68
10	10	213	21.12	163.82
10	10	219	21.85	174.42



 ${\it Stopband\ attenuation\ (dB),\ } A_s$  Figure 5: Plot of  $A_s$  versus  $D_p$  for ZW with different number of dips.




FIGURE 6: Plot of  $A_s$  versus D for ZW with different number of dips.

by taking an initial value of N=17, normalized passband frequency  $(f_p)=0.2$ , normalized stopband frequency  $(f_s)=0.3$ , and sampling frequency  $(F_s)=1$ . To design the ZWF, dips can be inserted anywhere between  $D_p$  and N/2. Dips are steered in the vicinity of  $D_p$  if small TBW is required, while

position of dips is moved towards N/2 if a large FESBA is needed. These design relationships are suitable up to  $A_s=175~\mathrm{dB}$  and L=10. However, if the desired SBA is more than 175 dB the number of dips may be increased by one for every 12–15 dB increment in SBA approximately. The limiting




FIGURE 7: Proposed flow chart to obtain the design relationships.

values of SBA range for different number of dips are shown in Table 2. Using Figures 5 and 6 following filter design relationships are obtained:

$$D_p = \begin{cases} 1, & A_s \leq 17, \\ 0.0273A_s + 0.5391, & 17 < A_s \leq 44, \\ 0.03612A_s + 0.0474, & 44 < A_s \leq 61, \\ 0.05073A_s - 0.089, & 61 < A_s \leq 77, \\ L, & 77 < A_s, \end{cases} \tag{8}$$
 
$$D = \begin{cases} 1.576, & A_s \leq 17, \\ 0.0682A_s + 0.6824, & 17 < A_s \leq 44, \\ 0.0718A_s - 0.6486 + L, & 44 < A_s. \end{cases}$$

These equations have been used to design FIR filters using ZW for a given set of specifications.

#### 4. Simulation Results and Discussion

The FIR filters using KW and ZW are simulated for establishing a comparative study as well as for determining the performance of the ZWF. Simulation results are shown in Figures 8, 9, and 10. ZWFs have been designed with one,

Table 2: Required number of dips and range of stopband attenuation.

Number of dips, L	Range of SBA, $A_s$ (dB)		
1	≤44		
2	≤61		
3	≤77		
4	≤92		
5	≤106		
6	≤120		
7	≤134		
8	≤148		
9	≤162		
10	≤175		

two, and three dips. Three sets of different  $A_p$  and  $A_s$  (i.e., 1.5 and 23 dB/0.1 and 50 dB/0.01 and 74 dB) have been used. The order of filter N, TBW, and FESBA has been recorded in Table 3 corresponding to these sets of  $A_p$  and  $A_s$ . ZWF response has been observed at the lower and upper bounds of dip positions, that is, at  $D_p$  and N/2. To establish a comparative study for every set of  $A_p$  and  $A_s$ , two KWFs have been designed: (i) with an order to satisfy the design




FIGURE 8: Frequency responses of LPF with  $f_p = 0.2$ ,  $f_s = 0.3$ ,  $A_p = 1.5$  dB, and  $A_s = 23$  dB with insertion of one dip, (a) comparative frequency responses, (b) expanded view of passband.




FIGURE 9: Frequency responses of LPF with  $f_p = 0.2$ ,  $f_s = 0.3$ ,  $A_p = 0.1$  dB, and  $A_s = 50$  dB with insertion of two dips, (a) comparative frequency responses, (b) expanded view of passband.




FIGURE 10: Frequency responses of LPF with  $f_p = 0.2$ ,  $f_s = 0.3$ ,  $A_p = 0.01$  dB,  $A_s = 74$  dB with insertion of three dips (a) comparative frequency responses (b) expanded view of passband.

specifications and (ii) with an order equal to the ZWF order. From the recorded observations the following conclusions regarding the filters performance have been drawn.

- (a) To satisfy desired set of filter specifications a comparatively lower filter order is required by KWF.
- (b) With dips steered at  $D_p$ , ZWF has a sharp TBW than KWF for the same filter order.
- (c) FESBA for a ZWF can be increased by increasing the number of dips and/or by translating the position of dips from  $D_p$  towards N/2.
- (d) For the same filter order ZWF provides greater FESBA than KWF by placing the dips at N/2.

This comparative study established the fact that a tradeoff can be achieved between TBW and FESBA for ZWFs by varying the number of dips and dip positions. To exploit this

S. no.	Type of filter	Number of dips, $L$	Position of dips	Filter order, N	Desired $A_p$ (dB)	Desired $A_s$ (dB)	Transition band	FESBA (dB)
	ZWF	1	$D_p$	23	1.5	23	0.0497	-36.59
1	ZWF	1	N/2	23	1.5	23	0.0770	-74.28
*	KWF	_	_	11	1.5	23	0.0861	-29.01
	$KWF(N_z)$	_	_	23	1.5	23	0.0652	-57.20
	ZWF	2	$D_p$	51	0.1	50	0.0624	-60.29
2	ZWF	2	N/2	51	0.1	50	0.0891	-133.1
-	KWF	_	_	31	0.1	50	0.0934	-78.97
	KWF $(N_z)$	_	-	51	0.1	50	0.0818	-104.4
	ZWF	3	$D_p$	77	0.01	74	0.0712	-86.85
3	ZWF	3	N/2	77	0.01	74	0.0892	-185.9
J	KWF	_	_	47	0.01	74	0.0988	-105.4
	$KWF(N_z)$	-	_	77	0.01	74	0.0824	-145.2

TABLE 3: Comparative performance of LPF.

ZWF: ZW based LPF; KWF: KW based LPF. KWF  $(N_z)$ : KW based filter with order of ZWF.




Figure 11: QMF filter banks with  $f_p = 0.15$ ,  $f_s = 0.25$ ,  $A_p = 0.01$  dB,  $A_s = 60$  dB (a) comparative frequency responses (b) reconstruction error and expanded view of the aliasing error in the inset.

feature of ZWFs they have been used as a prototype filters for QMF banks in the next section.

#### 5. ZWF Based QMF Bank

QMF bank has got wide applications in the area of signal processing specially in sub-band coding of speech signal, digital audio applications, communication systems, and short time spectral analysis [15]. In QMF bank, the input signal is split into two equally spaced frequency subbands by twoband analysis filters followed by twofold decimation. At the receiving end, the corresponding synthesis bank has twofold interpolation in both subbands followed by synthesis filters, and finally an adder is used to add both bands. The reconstructed output signal suffers from three types of distortions, that is, aliasing, amplitude or reconstruction, and phase distortion [15]. The aliasing error can be reduced by using a prototype filter with high FESBA, while the reconstruction error can be minimized using filters having sharp transition bands. As in ZW based filters, a tradeoff can be achieved between these two parameters, a QMF bank has been designed with ZWF as a prototype filter,

and their performance has been compared with KWF based QMF bank. To demonstrate its usefulness in this multirate signal processing application first lowpass prototype filters have been designed using ZW and KW with the following specifications:  $f_p = 0.15$ ,  $f_s = 0.25$ ,  $A_p = 0.01$  dB, and  $A_s = 60$  dB.

Then by using the optimization algorithm proposed by Soni et al. [16, 17] QMF banks have been designed. Corresponding frequency responses and error plots are shown in Figure 11. A comparative study has been carried out in Table 4. From this study it is observed that when dips are translated from  $D_p$  to N/2 aliasing error decreases. Optimum performance of ZWF based QMF banks has been obtained with dips steered at N/2, providing lowest values of reconstruction and aliasing errors. This performance is better than the KWF based QMF bank designed with the same filter order.

#### 6. Conclusion

A study on Z-windows has been carried out in this work by steering number of dips at different positions to characterize the variations in their HMLW, MSLL, and SLFOR. These

Type of QMF	Filter order, N	Reconstruction error (dB)	Aliasing error (dB)	FESBA (dB)
ZWF, dips at $D_p$	70	0.00649	$2.319 \times 10^{-3}$	-78.01
ZWF, dips at $N/10$	70	0.0172	$4.302 \times 10^{-6}$	-123.2
ZWF, dips at $N/6$	70	0.0127	$2.584 \times 10^{-7}$	-162.5
ZWF, dips at N/2	70	0.00934	$1.614 \times 10^{-7}$	-175.6
KWF	40	0.02349	$1.989 \times 10^{-4}$	-90.74
$KWZ(N_z)$	70	0.01243	$1.007 \times 10^{-6}$	-125.8

TABLE 4: Comparative performance of QMF bank.

window parameters have been chosen, as they proportionately decide the TBW, SBA, and FESBA parameters of filters. Since the number of dips and their positions together tailored the window shape, they have been compositely employed as a window shape parameter for ZW. The relationships (i) window shape parameter versus SBA and (ii) SBA versus D have been established to design a ZW based filter with desired specifications. Performance of ZWFs with different dip positions has been studied and compared with KWFs. For the same filter order ZWF provides a sharp TBW than KWF when dips are inserted at  $D_p,\,\mathrm{but}$  with small FESBA. Translation of dips from  $D_n$  towards N/2 results in a ZWF with better FESBA than KWF, but at the cost of relatively higher TBW. To exploit this trade-off between TBW and FESBA, ZWF has been used as a prototype filter to design a two-channel QMF bank using the optimization algorithm proposed by Soni et al. [16, 17]. Comparatively small distortion values in the ZWF based QMF bank have been obtained. Applicability of this filter can be further explored in other multirate signal processing applications.

#### References

- [1] L. R. Rabiner, J. F. Kaiser, O. Herrmann, and M. T. Dolan, "Some comparisons between FIR and IIR digital filters," *Bell System Technical Journal*, vol. 53, no. 2, pp. 305–331, 1974.
- [2] L. R. Rabiner and B. Gold, Theory and Applications of Digital Signal Processing, Prentice Hall, Englewood Cliffs, NJ, USA, 1975.
- [3] F. J. Harris, "On the use of windows for harmonic analysis with the discrete Fourier transform," *Proceedings of the IEEE*, vol. 66, no. 1, pp. 51–83, 1978.
- [4] J. K. Gautam, A. Kumar, and R. Saxena, "Windows: a tool in signal processing," *IETE Technical Review*, vol. 12, no. 3, pp. 217– 226, 1995.
- [5] F. I. Tseng, T. K. Sarkar, and D. D. Weiner, "A novel window for harmonic analysis," *IEEE Transactions on Acoustics, Speech, and Signal Processing*, vol. 29, no. 2, pp. 177–188, 1981.
- [6] J. Zhong, Z. Han, and W. Lu, "Design of windows with steerable sidelobe dips," *IEEE Transactions on Signal Processing*, vol. 40, no. 6, pp. 1452–1459, 1992.
- [7] S. N. Sharma, R. Saxena, and S. C. Saxena, "Design of narrow-band frequency sampling FIR filters using Z-window," Signal Processing, vol. 86, no. 11, pp. 3299–3308, 2006.
- [8] R. Pachauri, R. Saxena, and S. N. Sharma, "Design of FIR filters with better performance using Z-window," in Proceedings of the International Conference on Communications, Computing and Control Applications (CCCA '11), Hammamet, Tunisia, March 2011.

- [9] L. R. Rabiner, B. Gold, and C. A. McGonegal, "An approach to the approximation problem for nonrecursive digital filters," *IEEE Transactions on Audio and Electroacoustics*, vol. 18, no. 8, pp. 83–106, 1970.
- [10] L. R. Rabiner, "Linear program design of finite impulse response digital filters," *IEEE Transactions on Audio and Electroacoustics*, vol. 20, no. 4, pp. 280–288, 1972.
- [11] D. J. Defatta, J. G. Lucas, and W. S. Hodgkiss, *Digital Signal Processing: A System Design Approach*, John Wiley & Sons, 1995.
- [12] J. F. Kaiser, "Non-recursive digital filter design using the I<sub>0</sub>-Sinh window function," in *Proceedings of the IEEE International* Symposium on Circuits and Systems Proceedings, pp. 22–23, 1974.
- [13] K. M. M. Prabhu and K. Bhoopathy Bagan, "FIR digital filter design with variable parameter window families," *Journal of the Institution of Electronic and Radio Engineers*, vol. 58, no. 6, pp. 295–298, 1988.
- [14] S. N. Sharma, R. Saxena, and S. C. Saxena, "Design of FIR filters using variable window families: a comparative study," *Journal of the Indian Institute of Science*, vol. 84, no. 5, pp. 155–161, 2004.
- [15] P. P. Vaidyanathan, "Multirate digital filters, filter banks, polyphase networks, and applications: a tutorial," *Proceedings of the IEEE*, vol. 78, no. 1, pp. 56–93, 1990.
- [16] R. K. Soni, A. Jain, and R. Saxena, "The design of IFIR prototype filter for cosine modulated filter bank and transmultiplexer," *International Journal of Electronics and Communications*, vol. 67, no. 2, pp. 130–135, 2013.
- [17] R. K. Soni, A. Jain, and R. Saxena, "An optimized design of nonuniform filter bank using variable combinational window function," *International Journal of Electronics and Communica*tions, vol. 67, no. 7, pp. 595–601, 2013.

# Weather Forecasting Using Sliding Window Algorithm

## Piyush Kapoor<sup>1</sup> and Sarabjeet Singh Bedi<sup>2</sup>

1 Kvantum Inc., Gurgaon 122001, India

Correspondence should be addressed to Piyush Kapoor; piyushkapoor7@yahoo.com

Academic Editors: W.-L. Hwang and G. A. Tsihrintzis

To predict the future's weather condition, the variation in the conditions in past years must be utilized. The probability that the weather condition of the day in consideration will match the same day in previous year is very less. But the probability that it will match within the span of adjacent fortnight of previous year is very high. So, for the fortnight considered for previous year a sliding window is selected of size equivalent to a week. Every week of sliding window is then matched with that of current year's week in consideration. The window best matched is made to participate in the process of predicting weather conditions. The prediction is made based on sliding window algorithm. The monthwise results are being computed for three years to check the accuracy. The results of the approach suggested that the method used for weather condition prediction is quite efficient with an average accuracy of 92.2%.

#### 1. Introduction

Weather forecasting is mainly concerned with the prediction of weather condition in the given future time. Weather forecasts provide critical information about future weather. There are various approaches available in weather forecasting, from relatively simple observation of the sky to highly complex computerized mathematical models. The prediction of weather condition is essential for various applications. Some of them are climate monitoring, drought detection, severe weather prediction, agriculture and production, planning in energy industry, aviation industry, communication, pollution dispersal, and so forth, [1]. In military operations, there is a considerable historical record of instances when weather conditions have altered the course of battles. Accurate prediction of weather conditions is a difficult task due to the dynamic nature of atmosphere. The weather condition at any instance may be represented by some variables. Out of those variables, one found that the most significant are being selected to be involved in the process of prediction. The selection of variables is dependent on the location for which the prediction is to be made. The variables and their range always vary from place to place. The weather condition of any day has

some relationship with the weather condition existed in the same tenure of precious year and previous week.

A statistical model is designed [2] that could predict the rainfall and temperature with the help of past data by making use of time-delayed feed forward neural network. Artificial neural network was combined with the genetic algorithm to get the more optimized prediction [3]. An improved technique that uses artificial neural network with photovoltaic system was proposed by Isa et al. [4] that utilizes perceptron model with Levenberg Marquardt algorithm. Apart from neural network Fuzzy logic has also been being used in weather prediction models. The rainfall was classified into three fuzzy sets which can be predicted by making use of simple fuzzy rules [5]. Also a fuzzy self-regression model was proposed by Lu Feng and Xu xiao Guang [6] which makes use of the form of self-related sequence number according to observed number. The self-related coefficients were computed by making use of Fuzzy Logic [7]. A combined approach of neural network with Fuzzy Logic is being proposed for the weather prediction system. The work has applied principle component analysis technique to the fuzzy data by making use of Autoassociative neural networks.

<sup>&</sup>lt;sup>2</sup> MJP Rohilkhand University, Bareilly 243006, India